


TEA1009 TEA2014

TEA1009

Infra-red amplifier

Pin

- (1) 0 V ground
 - (2) 0 V ground
 - (3) 0 V ground
 - (4) 0 V ground
 - (5) 1V2
 - (6) → Data to decoder
 - (7) ← From pre amp section
 - (8) 0 V ground
 - (9) 3 V → Pre amp out
 - (10) ← 18 V supply
 - (11) 0V6
 - (12) 0 V ground
 - (13) 0V4 ← Input from infra-red diode
 - (14) 0 V ground
-



TEA2014

Video input selector

Pin

- (1) 0 V ground
 - (2) → 2 V pk-pk video
 - (3) ← 2 V pk-pk video from TV
 - (4)
 - (5) ← TV = 0 V, AV = 7 V switching control
 - (6) → Switched 2 V pk-pk video
 - (7) ← 12 V supply
 - (8) ← 1 V pk-pk video from SCART socket
-

